

## American Hakko Products, Inc.

## PRODUCT BULLETIN

Bulletin No: PB288

**Issue Date:** 5-20-2009

**Product Description:** Hakko FR-1012B IR Preheater

**Part No:** FR1012B-01



Specification:

opecincumon.		
Part No.	FR1012B-01	FR1012B-02
Board Capacity (Max.)	305 x 380 mm	
	(12 x 15 in.)	
Heating Area (Max.)	250 x 305 mm	
	(10 x 12 in.)	
Heating Zones	4 – Switch Controlled	
Heater Type	Low Mass Quartz IR Lamp Array	
Heater Power (Max.)	1200 W	
Control System	Industrial Microprocessor	
Temperature Control Modes	Power / Thermocouple	
Thermocouple Inputs	1 – Type K	
Power Consumption	100-120VAC - 10A	200-240VAC – 6A
Dimensions	360 x 460 x 130 mm	
$(W \times D \times H)$	(14 x 18 x 5 in.)	
Weight	7 kg (16 lb.)	

## Comments:

The Hakko FR-1012B IR Preheater replaces the Hakko FR-1012 IR Preheater. The differences between the two models are the addition of a switchable 4-zone heating array, a new 2 minute auto power off setting, improved cooling for reflected heat, and external access to electrical fuses.

FR-1012B IR Preheater

http://www.hakkousa.com/detail.asp?PID=4211&Page=1

Available:

June 1, 2009

For more information on the Hakko FR-1012B IR Preheater please visit our website at <a href="https://www.HakkoUSA.com">www.HakkoUSA.com</a>

From...

For additional information:

- End-User Customers Call Customer Support at 1-800-88-HAKKO (42556)
- Authorized Distributors Call Distributor Support at 661-294-0090

American Hakko Products, Inc. 28920 Avenue Williams. Valencia, CA 91355 Tel: (661) 294-0090 Fax: (661) 294-0096 www.HakkoUSA.com AHP14 Rev 2007-12