



American Hakko Products, Inc.

PRODUCT BULLETIN

Bulletin No: PB339

Issue Date: 7-25-2013


Available: 7-25-2013

Product Description:

Wireless Power Remote Control for
Hakko FA-430 Fume Extraction System

Part No:
999-252

Specification:

| | | |
|---------------------------------|----------|---|
| Unit Dimensions (L x W x H) | Receiver | 140 x 64 x 38 mm (5.5 x 2.5 x 1.5 in.) |
| | Remote | 69 x 38 x 23 mm (2.7 x 1.5 x 0.9 in.) |
| Shipping Dimensions (L x W x H) | | 254 x 153 x 76 mm (10 x 6 x 3 in.) |
| Unit Weight | Receiver | 176 g (0.39 lb.) |
| | Remote | 36 g (0.08 lb.) |
| Shipping Weight | | 354 g (0.78 lb.) |
| Voltage | | 125VAC / 60Hz |
| Max Load | | 13A 1625W Resistive 8A 1000W Tungsten |
| Cord Length | | 153mm (6 in.) |
| Cord Type | | 3-wire 16AWG Stranded |
| Remote Battery | | 12VDC Type A23 |
| Range | | Up to 60ft. |
| Safety Certification | |  |



Comment:

The Hakko 999-252 Wireless Remote is a convenient accessory to the Hakko FA-430 Fume Extraction System. By placing the wireless remote inline between the FA-430 and the power outlet, you can easily turn the fume extraction system on or off at the push of a button. No need to reach under or behind the bench for the power switch on the front of the Hakko FA-430, and no added cords or wires on the bench top like other remote switches.

NOTE: Each unit is encoded for a set transmit/receive frequency as indicated by the small sticker affixed to each receiver and remote control. The channels are labeled A, B, C, D, E, or F. If you have multiple units that are using the same encoded frequency and are within the range of the like coded remote control, all units can be controlled simultaneously by one remote.

For more information, visit us online at www.HakkoUSA.com or call us at 1-800-88-HAKKO (42556).

AHP14 Rev 2012-11