



American Hakko Products, Inc.

PRODUCT BULLETIN

Bulletin No: PB314

Issue Date: 7-25-2011

Available: 7-25-2011

Product Description:

Hakko FT-8002 Conversion Kit

Part No:

FT8002-CK

Specification:

Kit Specifications	
Part No.	FT8002-CK
Power Consumption	64W 24VAC
Tip-to-Ground	< 2 Ω
Leak Voltage	< 2 mV
Length (w/o cord, blade)	96 mm (3.8 in.)
Weight (w/ cord, blade)	48 g (0.11 lb)
Reach	1.3 m (4.3 ft)
Blades	G2 Series

NOTE: G2 Blades are not included

Kit Contents	
Part No.	Description
FT8002-01	FT-8002 Handpiece
C1573	FT-8002 Handpiece Holder
B3644	FT-8002 Lead Adjuster
B3648	Blade Removal Tool

IMPORTANT:

Sleep and Auto Power Off functions are disabled when using the FT8002-CK.



Comments:

The HAKKO FT-8002 Conversion Kit allows existing FT-800 users to use the improved FT-8002 handpiece for better operator comfort, durability, and cooler operation. The FT-8002 Handpiece also uses the new G2 Series blades, which have improved durability over the previous G1 Series blades.

It is recommended that customers use this conversion kit when switching to G2 Series blades since the use of G2 blades in older FT-8001 Handpieces may exhibit rotational play when inserted. This is due to the wear of the resin on the older handpiece.

Older G1 Series blades may be used in the improved FT-8002 handpiece, however the alignment blocks on the body of the blades may require minor adjustment to ensure proper alignment.

For more information, please visit our web site at www.HakkoUSA.com.

From...

For additional information:

- End-User Customers – Call Customer Support at 1-800-88-HAKKO (42556)
- Authorized Distributors – Call Distributor Support at 661-294-0090

American Hakko Products, Inc.
 28920 Avenue Williams.
 Valencia, CA 91355
 Tel: (661) 294-0090
 Fax: (661) 294-0096
www.HakkoUSA.com
 AHP14 Rev 2007-12